


DJM-V5

NEXT-GENERATION 3-CHANNEL DJ MIXER

- Compact design
- 4-band EQ
- 60-mm faders
- High-resolution sound
- Send FX
- 3 filter types
- Built-in SonicLink transmitter
- PRO DJ LINK support
- Extensive compatibility
- 2-Band Booth EQ



DJM-V5 // NEXT-GENERATION 3-CHANNEL DJ MIXER



SPECIFICATIONS

Software		rekordbox for Mac/Windows Serato DJ Pro (license needed)
Frequency Response		20 Hz – 40 kHz (LINE)
S/N Ratio		110 dB (USB) 105 dB (LINE) 88 dB (PHONO) 79 dB (MIC)
Total Harmonic Distortion		0.005 % (LINE-MASTER)
Input/Output Terminals	Inputs	LINE × 3 (RCA) PHONO × 3 (RCA) RETURN × 1 (1/4" TS jack) MIC × 1 (XLR & 1/4" TRS jack)
	Outputs	MASTER × 1 (XLR) BOOTH × 1 (1/4" TRS jack) SEND × 1 (1/4" TS jack) HEADPHONE MONITOR × 2 (1/4" stereo jack × 1, 3.5-mm stereo mini jack × 1) REC × 1 (RCA)
	USB	USB (Type-C) × 2
	Others	LINK (LAN) × 1
	SonicLink (Headphones Output)	Frequency Band Used: 2.4 GHz
Maximum Dimensions (W × D × H)		302.0 × 437.5 × 107.9 mm / 11.89" × 17.22" × 4.25"
Weight		8.0 kg / 17.6 lb.
Accessories		Power cord Quick Start Guide Precautions for Use Warranty (for some regions)

PRODUCT FEATURES



Compact design

The DJM-V5 inherits the layout, tactile feel, and many features of the DJM-V10 – including the 4-band EQ, compressor, filter, and Send FX – but has a 30% smaller footprint. It also includes the 60-mm long-throw channel faders from the DJM-V10-LF for precise level control.



3 filter types

Each channel features a dedicated filter knob with 3 selectable modes: low-pass, high-pass, and cross-pass. The knob's left-to-right sweep structure gives you both subtle and dynamic control.



High-resolution sound

The mixer delivers well-balanced mixing that avoids sonic saturation – even when you layer multiple audio sources. It features studio-grade 96 kHz / 64-bit mixing DSP processing, with high-quality 32-bit A/D and D/A converters from ESS Technology built into the channel input and master output sections.



Built-in SonicLink transmitter

Pair the mixer with the HDJ-F10 headphones at the press of a button. For headphone models scheduled for release in 2026, pairing will be possible by touching the headphone area on the front panel of the DJM-V5.



Send FX

Add texture to your music with 6 expressive effects: Short Delay, Reverb, Shimmer, Tape Echo, PingPong, and Echo-Verb. Each channel features a dedicated send knob so you can intuitively adjust the amount of effect applied to individual tracks.



Extensive compatibility

Connect the rear USB Type-C terminal to a PC/Mac running rekordbox or Serato DJ Pro^{*1}. The MULTI I/O also features a top-panel USB Type-C port to connect an iPhone or iPad^{*2} to use DJM-REC or connect the RMX-IGNITE. The unit also supports insert connections with an external effector via USB send/return.

* Disclaimer: Specifications and price are subject to change.

* rekordbox™ is a trademark or registered trademark of AlphaTheta Corporation.

* Other product, technology, and company names, etc. mentioned herein are trademarks or registered trademarks of their respective owners.

*1 You'll need a separate license to use Serato DJ Pro.

*2 Only compatible with iPhone or iPad equipped with a USB Type-C port.