

RMX-IGNITE

NEXT-GENERATION
EFFECTOR

Take your performances higher

- 3-Band FX section
- Lever FX
- Isolate FX
- Sampler section
- Sample Roll
- Sampler Color FX
- Release Echo
- Multicolor screen
- PRO DJ LINK support
- Digital send/return
- Professional sound design



RMX-IGNITE // NEXT-GENERATION EFFECTOR

Take your performances higher

SPECIFICATIONS

Compatible Software	RMX-IGNITE Sample Manager	
Sampling Rate	96 kHz	
A/D, D/A Converter	32 bit	
Frequency Response	20 Hz – 40 kHz	
S/N Ratio (rated output, A-WEIGHTED)	CONNECTION switch (MST): 115 dB CONNECTION switch (SEND/RETURN): 114 dB CONNECTION switch (CDJ): 108 dB	
Total Harmonic Distortion (20 Hz – 20 kHz BW)	0.0018%	
Input/Output Terminals	Input	1/4" TS jack x 1
	Output	1/4" TS jack x 1
	USB	USB Type-A x 1 USB Type-C x 2
	Others	LAN port (100BASE-TX) x 1
Power Requirements	AC100 V – 240 V, 50 Hz/60 Hz	
Maximum Dimensions (WxDxH)	340.0 x 213.3 x 72.8 mm / 13.4" x 8.4" x 2.9"	
Main Unit Weight	2.3 kg / 5.1 lb	
Accessories	AC adapter x 1 Power cord x 1 Warranty (for some regions)* x 1 Quick Start Guide x 1 Precautions for Use x 1	
	* Only products in Europe. Products in North America and Japan include warranty information in the Precautions for Use.	

PRODUCT FEATURES




3-Band FX section

The 3-Band FX section includes 2 types of effects: Lever FX and Isolate FX. You can apply each to the high, mid, and low frequency bands independently, and freely combine up to 6 types of effects. With sub-parameter knobs for tonal adjustment, you can shape track progressions and deliver rich, expressive performances.



Sampler section

The unit comes preloaded with 20 samples from Loopcloud and, using the dedicated RMX-IGNITE Sample Manager software, you can export your own samples to a USB drive and insert it into the unit, or into a DJ player connected via a PRO DJ LINK network, and drop the sounds into your sets.



Release Echo

With one large button, you can instantly reset effects and samples you've applied, smoothly returning to the original track with an echo tail.




Pro DJ LINK support

By syncing BPM and grid information with tracks playing on CDJs and other DJ players, the effector ensures accurate beat alignment when you're using roll and overdub. You can also load samples directly from USB drives or SD cards plugged into players connected via PRO DJ LINK.¹



Digital send/return

The RMX-IGNITE supports digital send/return connections with the DJM-A9 and DJM-V10 mixers. Simply connect a single USB cable to the MULTI I/O terminal on a compatible mixer for quick setup and high-quality sound.²



Professional sound quality

The completely redesigned audio architecture delivers significantly improved sound quality.

* Disclaimer: Specifications and price are subject to change.

* Other product, technology, and company names, etc. mentioned herein are trademarks or registered trademarks of their respective owners.

1. To use PRO DJ LINK, the firmware of connected DJ players must be updated to the latest version.

2. To use digital send/return, the firmware of the compatible DJ mixer must be updated to the latest version.



AlphaTheta EMEA Limited | Unit 39, Tileyard Studios, Tileyard Road, London, N7 9AH, UK | +44 (0) 203 761 7220
AlphaTheta Music Americas, Inc. | 2050 W. 190th Street, Suite 109, CA 90504, Torrance, USA | +1 (424) 488-0480
AlphaTheta Corporation | 6-F, Yokohama i-Mark Place, 4-4-5 Minatomirai, Nishi-ku, Yokohama, Kanagawa 220-0012 Japan | +81 045-522-5400



ALPHATHETA.COM