




151.804 V1.1

DOTBAR CYC1

QUICK START GUIDE

CONTROL MENU

If the display is in standby, unlock it:



MENU			DESCRIPTION
SET UP	Dimmer All	000-255	Master dimmer
	White Balance	Red	000-255
		Green	000-255
		Blue	000-255
	Dimmer Speed	Speed 1-5	Dimmer speed
	Key lock	Off /On	+/-/+/-/Enter
		On	Activate key lock yes/no
	Display	30S	Display sleep mode or on
		On	
	Max Temp	Choose between 30 -65°C	+/-/+/-/Enter
INFORMATION	Software Ver	***	Shows software version
	RDM UID		Shows RDM address
	Working time	*****H**M	Shows Working hours
	Hardware Ver		Shows hardware version
	FACTORY RESET	+/-/+/-/Enter	Reset mode
DMX MODE	Address	001-512	Select a DMX Channel
	Channel	3CH,7CH,11CH,48CH,53CH	Select a Channel mode
DIMMER CURVE		Linear,Square Law,Inv.Squ.Law,S-Curve	
DMX STATE		Hold/ Blackout	Select what to do when there is no DMX signal input.
SLAVE MODE		Slave / Master	Select slave / master mode
AUTO MODE	Speed	01-30	Select speed auto mode
	Auto	01-13	Select different auto mode
STATIC COLOR	Red	000-255	Adjust dimming
	Green	000-255	
	Blue	000-255	
	Color	01-63	Adjust Color
	Strobe	00-20	Adjust strobe
CCT		2700/3200/3500/4000/4500/5000/5600/ 6000/6500/7000/7500K/8000K	Adjust CCT

DMX CHANNELS

3 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	HUE	000-255	Hue
2	SATURATION	000-255	Saturation
3	VALUE	000-255	Value

7 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000- 255	Dimmer
2	DIMMER CURVE	001-063	Linear
		064-127	Square Law
		128-191	Inv.Squ.Law
		192-255	S-Curve
3	DIMMER SPEED	000-005	No Function
		006-055	Dimmer Speed1
		056-105	Dimmer Speed2
		106-155	Dimmer Speed3
		156-205	Dimmer Speed4
		206-255	Dimmer Speed5
4	RED	000-255	Red
5	GREEN	000-255	Green
6	BLUE	000-255	Blue
7	STROBE	000-009	No function
		010-021	Strobe1
		022-033	Strobe2
		034-045	Strobe3
		046-057	Strobe4
		058-069	Strobe5
		070-081	Strobe6
		082-093	Strobe7
		094-105	Strobe8
		106-117	Strobe9
		118-129	Strobe10
		130-141	Strobe11
		142-153	Strobe12
		154-165	Strobe13
		166-177	Strobe14
		178-189	Strobe15
		190-201	Strobe16
		202-213	Strobe17
		214-225	Strobe18
		226-237	Strobe19
		238-255	Strobe20

11 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Dimmer
2	DIMMER CURVE	001-063	Linear
		064-127	Square Law
		128-191	Inv.Squ.Law
		192-255	S-Curve
3	DIMMER SPEED	000-005	No Function
		006-055	Dimmer Speed1
		056-105	Dimmer Speed2
		106-155	Dimmer Speed3
		156-205	Dimmer Speed4
		206-255	Dimmer Speed5
4	RED	000-255	Red
5	GREEN	000-255	Green
6	BLUE	000-255	Blue
7	STROBE	000-009	No function
		010-021	Strobe1
		022-033	Strobe2
		034-045	Strobe3
		046-057	Strobe4
		058-069	Strobe5
		070-081	Strobe6
		082-093	Strobe7
		094-105	Strobe8
		106-117	Strobe9
		118-129	Strobe10
		130-141	Strobe11
		142-153	Strobe12
		154-165	Strobe13
		166-177	Strobe14
		178-189	Strobe15
		190-201	Strobe16
		202-213	Strobe17
		214-225	Strobe18
		226-237	Strobe19
8	COLOR	238-255	Strobe20
		000-007	No function
		008-011	Color1
		012-015	Color2
		016-019	Color3
		020-023	Color4
		024-027	Color5
		028-031	Color6
		032-035	Color7
		036-039	Color8
		040-043	Color9
		044-047	Color10
		048-051	Color11
		052-055	Color12
		056-059	Color13
		060-063	Color14

			064-067	Color15
			068-071	Color16
			072-075	Color17
			076-079	Color18
			080-083	Color19
			084-087	Color20
			088-091	Color21
			092-095	Color22
			096-099	Color23
			100-103	Color24
			104-107	Color25
			108-111	Color26
			112-115	Color27
			116-119	Color28
			120-123	Color29
			124-127	Color30
			128-131	Color31
			132-135	Color32
			136-139	Color33
			140-143	Color34
			144-147	Color35
			148-151	Color36
			152-155	Color37
			156-159	Color38
			160-163	Color39
			164-167	Color40
			168-171	Color41
			172-175	Color42
			176-179	Color43
			180-183	Color44
			184-187	Color45
			188-191	Color46
			192-195	Color47
			196-199	Color48
			200-203	Color49
			204-207	Color50
			208-211	Color51
			212-215	Color52
			216-219	Color53
			220-223	Color54
			224-227	Color55
			228-231	Color56
			232-235	Color57
			236-239	Color58
			240-243	Color59
			244-247	Color60
			248-251	Color61
			252-255	Color62
9	CCT	000-015	No function	
		016-035	2700K	
		036-055	3200K	
		056-075	3500K	

		076-095	4000K
		096-115	4500K
		116-135	5000K
		136-155	5600K
		156-175	6000K
		176-195	6500K
		196-215	7000K
		216-235	7500K
		236-255	8000K
10	AUTO	000-007	No function
		008-027	Auto1
		028-047	Auto2
		048-067	Auto3
		068-087	Auto4
		088-107	Auto5
		108-127	Auto6
		128-147	Auto7
		148-167	Auto8
		168-187	Auto9
		188-207	Auto10
		208-227	Auto11
		228-247	Auto12
		248-255	Auto13
11	AUTO SPEED	001-007	Auto Speed1
		008-015	Auto Speed2
		016-023	Auto Speed3
		024-031	Auto Speed4
		032-039	Auto Speed5
		040-047	Auto Speed6
		048-055	Auto Speed7
		056-063	Auto Speed8
		064-071	Auto Speed9
		072-079	Auto Speed10
		080-087	Auto Speed11
		088-095	Auto Speed12
		096-103	Auto Speed13
		104-111	Auto Speed14
		112-119	Auto Speed15
		120-127	Auto Speed16
		128-135	Auto Speed17
		136-143	Auto Speed18
		144-151	Auto Speed19
		152-159	Auto Speed20
		160-167	Auto Speed21
		168-175	Auto Speed22
		176-183	Auto Speed23
		184-191	Auto Speed24
		192-199	Auto Speed25
		200-207	Auto Speed26
		208-215	Auto Speed27
		216-223	Auto Speed28
		224-231	Auto Speed29

48 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Red1	000-255	Red1
2	Green1	000-255	Green1
3	Blue1	000-255	Blue1
4	Red2	000-255	Red2
5	Green2	000-255	Green2
6	Blue2	000-255	Blue2
7	Red3	000-255	Red3
8	Green3	000-255	Green3
9	Blue3	000-255	Blue3
10	Red4	000-255	Red4
11	Green4	000-255	Green4
12	Blue4	000-255	Blue4
13	Red5	000-255	Red5
14	Green5	000-255	Green5
15	Blue5	000-255	Blue5
16	Red6	000-255	Red6
17	Green6	000-255	Green6
18	Blue6	000-255	Blue6
19	Red7	000-255	Red7
20	Green7	000-255	Green7
21	Blue7	000-255	Blue7
22	Red8	000-255	Red8
23	Green8	000-255	Green8
24	Blue8	000-255	Blue8
25	Red9	000-255	Red9
26	Green9	000-255	Green9
27	Blue9	000-255	Blue9
28	Red10	000-255	Red10
29	Green10	000-255	Green10
30	Blue10	000-255	Blue10
31	Red11	000-255	Red11
32	Green11	000-255	Green11
33	Blue11	000-255	Blue11
34	Red12	000-255	Red12
35	Green12	000-255	Green12
36	Blue12	000-255	Blue12
37	Red13	000-255	Red13
38	Green13	000-255	Green13
39	Blue13	000-255	Blue13
40	Red14	000-255	Red14
41	Green14	000-255	Green14
42	Blue14	000-255	Blue14
43	Red15	000-255	Red15
44	Green15	000-255	Green15
45	Blue15	000-255	Blue15
46	Red16	000-255	Red16
47	Green16	000-255	Green16
48	Blue16	000-255	Blue16

53 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Dimmer
2	Dimmer Curve	001-063	Linear
		064-127	Square Law
		128-191	Inv.Squ.Law
		192-255	S-Curve
3	Dimmer Speed	000-005	No function
		006-055	Dimmer Speed1
		056-105	Dimmer Speed2
		106-155	Dimmer Speed3
		156-205	Dimmer Speed4
		206-255	Dimmer Speed5
4	Auto	000-007	No function
		008-027	Auto1
		028-047	Auto2
		048-067	Auto3
		068-087	Auto4
		088-107	Auto5
		108-127	Auto6
		128-147	Auto7
		148-167	Auto8
		168-187	Auto9
		188-207	Auto10
		208-227	Auto11
		228-247	Auto12
		248-255	Auto13
5	Auto Speed	001-007	Auto Speed1
		008-015	Auto Speed2
		016-023	Auto Speed3
		024-031	Auto Speed4
		032-039	Auto Speed5
		040-047	Auto Speed6
		048-055	Auto Speed7
		056-063	Auto Speed8
		064-071	Auto Speed9
		072-079	Auto Speed10
		080-087	Auto Speed11
		088-095	Auto Speed12
		096-103	Auto Speed13
		104-111	Auto Speed14
		112-119	Auto Speed15
		120-127	Auto Speed16
		128-135	Auto Speed17
		136-143	Auto Speed18
		144-151	Auto Speed19
		152-159	Auto Speed20
		160-167	Auto Speed21
		168-175	Auto Speed22
		176-183	Auto Speed23
		184-191	Auto Speed24
		192-199	Auto Speed25

		200-207	Auto Speed26
		208-215	Auto Speed27
		216-223	Auto Speed28
		224-231	Auto Speed29
		232-255	Auto Speed30
6	Red1	000-255	Red1
7	Green1	000-255	Green1
8	Blue1	000-255	Blue1
9	Red2	000-255	Red2
10	Green2	000-255	Green2
11	Blue2	000-255	Blue2
12	Red3	000-255	Red3
13	Green3	000-255	Green3
14	Blue3	000-255	Blue3
15	Red4	000-255	Red4
16	Green4	000-255	Green4
17	Blue4	000-255	Blue4
18	Red5	000-255	Red5
19	Green5	000-255	Green5
20	Blue5	000-255	Blue5
21	Red6	000-255	Red6
22	Green6	000-255	Green6
23	Blue6	000-255	Blue6
24	Red7	000-255	Red7
25	Green7	000-255	Green7
26	Blue7	000-255	Blue7
27	Red8	000-255	Red8
28	Green8	000-255	Green8
29	Blue8	000-255	Blue8
30	Red9	000-255	Red9
31	Green9	000-255	Green9
32	Blue9	000-255	Blue9
33	Red10	000-255	Red10
34	Green10	000-255	Green10
35	Blue10	000-255	Blue10
36	Red11	000-255	Red11
37	Green11	000-255	Green11
38	Blue11	000-255	Blue11
39	Red12	000-255	Red12
40	Green12	000-255	Green12
41	Blue12	000-255	Blue12
42	Red13	000-255	Red13
43	Green13	000-255	Green13
44	Blue13	000-255	Blue13
45	Red14	000-255	Red14
46	Green14	000-255	Green14
47	Blue14	000-255	Blue14
48	Red15	000-255	Red15
49	Green15	000-255	Green15
50	Blue15	000-255	Blue15
51	Red16	000-255	Red16
52	Green16	000-255	Green16



53	Blue16	000-255	Blue16
----	--------	---------	--------







BEAMZ

YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT

 **beamZ^{Pro}**

offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!



BEAMZLIGHTING.COM