

Power Dynamics PDW500MP3

Power Dynamics PDW500MP3 è un amplificatore PA mixer da 500W con lettore MP3, ideale per sistemi audio multi-zona in ambienti commerciali e pubblici.



Prezzo di listino:	459,00 €
Prezzo:	435,00 €
Disponibile:	Ordinabile dal 28/09/2026
Consegna in:	-
Spedizione:	Gratis in Italia
Marchio:	Power dynamics
Categoria:	Amplificatori per installazioni
Condizione:	Nuovo
Link articolo	

- Amplificatore PA con 6 zone e controlli di volume separati
- Lettore multimediale con sintonizzatore FM, USB e slot SD
- Ricevitore BT per lo streaming audio
- Amplificatore in classe D da 500 W
- 100V/70V o 16, 8, 4 Ohm
- Controllo del volume di zona
- Controllo bassi/acuti/echo
- Display LCD digitale
- Ingresso microfono XLR con alimentazione phantom commutabile (24 V)
- Ingresso microfono da 6,3 mm con priorità
- 2 ingressi di linea RCA e 1 uscita di linea RCA
- Montabile su rack da 19" (2U)
- Playback options
- BT streaming, FM radio, SD, USB
- Output power: Max 500W
- Output power: RMS 400W
- Impedance 100V, 16 Ohm, 4 Ohm, 70V, 8 Ohm
- Frequency response 100Hz - 19.000Hz
- Signal-to-noise ratio: Line >85dB
- Signal-to-noise ratio: Mic >80dB
- Power supply 100-240VAC 50/60Hz
- Input level: Line 400mV
- Input level: Mic. 10mV
- THD <1%
- Dimensions (L x W x H) 310 x 420 x 95 mm (with rack ears: 480 mm)
- Weight 9,90
- Accessories Mounting bracket, Power cable